

## DMX Patch

Venue: E-Werk Erlangen Saal / Big Venue Date: 11.09.2019

Fix-ID	Position	Manufacturer	Model	Patch	Mode	Notes
	Fronttruss	ARRI	ST1 Fresnel 1kW	1.080		p.o.
	Fronttruss	ARRI	ST1 Fresnel 1kW	1.084		p.o.
	Fronttruss	ARRI	ST1 Fresnel 1kW	1.091		p.o.
	Fronttruss	ARRI	ST1 Fresnel 1kW	1.095		p.o.
	Midtruss	ARRI	ST1 Fresnel 1kW	1.074		p.o.
	Midtruss	ARRI	ST1 Fresnel 1kW	1.075		p.o.
	Side DSL	ARRI	ST1 Fresnel 1kW	1.070		p.o.
	Side DSR	ARRI	ST1 Fresnel 1kW	1.061		p.o.
	Side USL	ARRI	ST1 Fresnel 1kW	1.069		p.o.
	Side USR	ARRI	ST1 Fresnel 1kW	1.063		p.o.

	Fronttruss	ETC	Source 4 Zoom 25-50°	1.079		with Iris
	Fronttruss	ETC	Source 4 Zoom 25-50°	1.083		with Iris
	Fronttruss	ETC	Source 4 Zoom 25-50°	1.087		with Iris
	Fronttruss	ETC	Source 4 Zoom 25-50°	1.090		with Iris
	Fronttruss	ETC	Source 4 Zoom 25-50°	1.092		with Iris
	Fronttruss	ETC	Source 4 Zoom 25-50°	1.096		with Iris

	Backtruss	Generic/Major	6Bar 6x PAR64 1kW CP60	1.001	-1.006	std. N.C.!
	Backtruss	Generic/Major	6Bar 6x PAR64 1kW CP60	1.007	-1.012	std. N.C.!

	Midpipe	Generic/Major	2Lite DWE	1.073		
	Midpipe	Generic/Major	2Lite DWE	1.076		
	Midtruss	Generic/Major	2Lite DWE	1.064		
	Midtruss	Generic/Major	2Lite DWE	1.067		
	Backtruss	Generic/Major	2Lite DWE	1.057		
	Backtruss	Generic/Major	2Lite DWE	1.056		

	Fronttruss	Generic/Major	4Lite DWE 1 - left side	1.081		
	Fronttruss	Generic/Major	4Lite DWE 1 - right side	1.082		
	Fronttruss	Generic/Major	4Lite DWE 2 - left side	1.085		
	Fronttruss	Generic/Major	4Lite DWE 2 - right side	1.086		
	Fronttruss	Generic/Major	4Lite DWE 3 - left side	1.088		
	Fronttruss	Generic/Major	4Lite DWE 3 - right side	1.089		
	Fronttruss	Generic/Major	4Lite DWE 4 - left side	1.093		
	Fronttruss	Generic/Major	4Lite DWE 4 - right side	1.094		

	Midtruss	Generic/Major	PAR36 ACL 2x4	1.068		
	Backtruss	Generic/Major	PAR36 ACL 2x4	1.055		

	HOUSE	ERCO	Houselight (3 Areal)	1.133	3 Channels!	std. N.C.!
--	-------	------	----------------------	-------	-------------	------------

<b>Fix-ID</b>	<b>Position</b>	<b>Manufacturer</b>	<b>Model</b>	<b>Patch</b>	<b>Mode</b>	<b>Notes</b>
	Backtruss	ClayPaky	Axcor Spot 400	2.001	28 Ch.	Show only!
	Backtruss	ClayPaky	Axcor Spot 400	2.029	28 Ch.	Show only!
	Backtruss	ClayPaky	Axcor Spot 400	2.057	28 Ch.	Show only!
	Backtruss	ClayPaky	Axcor Spot 400	2.085	28 Ch.	Show only!
	Backtruss	ClayPaky	Axcor Spot 400	2.113	28 Ch.	Show only!
	Midtruss	ClayPaky	Axcor Spot 400	2.141	28 Ch.	Show only!
	Midtruss	ClayPaky	Axcor Spot 400	2.169	28 Ch.	Show only!
	Midtruss	ClayPaky	Axcor Spot 400	2.197	28 Ch.	Show only!
	Midtruss	ClayPaky	Axcor Spot 400	2.225	28 Ch.	Show only!
	Midtruss	ClayPaky	Axcor Spot 400	2.253	28 Ch.	Show only!

	Backtruss	ClayPaky	B-EYE K10	3.001	Shapes 34Ch.	Show only!
	Backtruss	ClayPaky	B-EYE K10	3.036	Shapes 34Ch.	Show only!
	Backtruss	ClayPaky	B-EYE K10	3.071	Shapes 34Ch.	Show only!
	Backtruss	ClayPaky	B-EYE K10	3.106	Shapes 34Ch.	Show only!
	Midtruss	ClayPaky	B-EYE K10	3.141	Shapes 34Ch.	Show only!
	Midtruss	ClayPaky	B-EYE K10	3.176	Shapes 34Ch.	Show only!
	Midtruss	ClayPaky	B-EYE K10	3.211	Shapes 34Ch.	Show only!
	Midtruss	ClayPaky	B-EYE K10	3.246	Shapes 34Ch.	Show only!
	Midpipe	ClayPaky	B-EYE K10	3.281	Shapes 34Ch.	Show only!
	Midpipe	ClayPaky	B-EYE K10	3.316	Shapes 34Ch.	Show only!
	Midpipe	ClayPaky	B-EYE K10	3.351	Shapes 34Ch.	Show only!
	Midpipe	ClayPaky	B-EYE K10	3.386	Shapes 34Ch.	Show only!

	Midpipe SR	Martin Pro	Atomic 3000 DMX	5.421	Effect (4Ch.)	Show only!
	Midpipe SL	Martin Pro	Atomic 3000 DMX	5.425	Effect (4Ch.)	Show only!
	Dancefloor	Martin Pro	Atomic 3000 DMX	4.198	Effect (4Ch.)	Disko only!
	Dancefloor	Martin Pro	Atomic 3000 DMX	4.202	Effect (4Ch.)	Disko only!

	Dancefloor	JB-Lighting	JBLED A4	4.001	S16 (19Ch.)	Disko only!
	Dancefloor	JB-Lighting	JBLED A4	4.020	S16 (19Ch.)	Disko only!
	Dancefloor	JB-Lighting	JBLED A4	4.039	S16 (19Ch.)	Disko only!
	Dancefloor	JB-Lighting	JBLED A4	4.058	S16 (19Ch.)	Disko only!
	Dancefloor	JB-Lighting	JBLED A4	4.077	S16 (19Ch.)	Disko only!
	Dancefloor	JB-Lighting	JBLED A4	4.096	S16 (19Ch.)	Disko only!
	Dancefloor	JB-Lighting	JBLED A4	4.115	S16 (19Ch.)	Disko only!
	Dancefloor	JB-Lighting	JBLED A4	4.134	S16 (19Ch.)	Disko only!
	Dancefloor	JB-Lighting	JBLED A4	4.153	S16 (19Ch.)	Disko only!

	Dancefloor	Elation	Platinum Spot LED	4.229	M2 (16Ch.)	Disko only!
	Dancefloor	Elation	Platinum Spot LED	4.245	M2 (16Ch.)	Disko only!
	Dancefloor	Elation	Platinum Spot LED	4.261	M2 (16Ch.)	Disko only!
	Dancefloor	Elation	Platinum Spot LED	4.277	M2 (16Ch.)	Disko only!
	Dancefloor	Elation	Platinum Spot LED	4.293	M2 (16Ch.)	Disko only!
	Dancefloor	Elation	Platinum Spot LED	4.309	M2 (16Ch.)	Disko only!
	Dancefloor	Elation	Platinum Spot LED	4.325	M2 (16Ch.)	Disko only!
	Dancefloor	Elation	Platinum Spot LED	4.341	M2 (16Ch.)	Disko only!

<b>Fix-ID</b>	<b>Position</b>	<b>Manufacturer</b>	<b>Model</b>	<b>Patch</b>	<b>Mode</b>	<b>Notes</b>
	Dancefloor	Elation	Platinum Beam 5R	4.172	STD. (13Ch.)	Disko only!
	Dancefloor	Elation	Platinum Beam 5R	4.185	STD. (13Ch.)	Disko only!

		Ignition	Magic Cube 3D	4.357	17 Channel	Disko only!
		Ignition	Magic Cube 3D	4.374	17 Channel	Disko only!
		Ignition	Magic Cube 3D	4.391	17 Channel	Disko only!
		Ignition	Magic Cube 3D	4.408	17 Channel	Disko only!
		Ignition	Magic Cube 3D	4.425	17 Channel	Disko only!
		Ignition	Magic Cube 3D	4.442	17 Channel	Disko only!

	Empore FOH-L	Eurolite	LEDBar 252/2		EFX (12Ch.)	
	Empore FOH-L	Eurolite	LEDBar 252/2		EFX (12Ch.)	
	Empore FOH-L	Eurolite	LEDBar 252/2		EFX (12Ch.)	
	Empore FOH-L	Eurolite	LEDBar 252/2		EFX (12Ch.)	
	Empore FOH-R	Eurolite	LEDBar 252/2		EFX (12Ch.)	
	Empore FOH-R	Eurolite	LEDBar 252/2		EFX (12Ch.)	
	Empore FOH-R	Eurolite	LEDBar 252/2		EFX (12Ch.)	
	Empore FOH-R	Eurolite	LEDBar 252/2		EFX (12Ch.)	

	Fronttruss SR	Look Solutions	Viper 2.6. - w/ hanging	4.502	STD. (1Ch.)	Disko only!
	Fronttruss SL	Look Solutions	Viper 2.6. - w/ hanging	4.503	STD. (1Ch.)	Disko only!
	Floor USR	Smoke Factory	Tourhazer II DMX	4.500	STD (2Ch.)	
	Floor USL	Smoke Factory	Tourhazer II DMX	4.500	STD (2Ch.)	

**DMX Chart: ClayPaky Axcor Spot 400**

1	CYAN
2	MAGENTA
3	YELLOW
4	CTO
5	COLOR WHEEL
6	STROBE
7	DIMMER
8	DIMMER FINE
9	IRIS
10	ROTATING GOBO 1 CHANGE
11	GOBO 1 ROTATION
12	GOBO 1 ROTATION FINE
13	ROTATING GOBO 2 CHANGE
14	GOBO 2 ROTATION
15	GOBO 2 ROTATION FINE
16	PRISM INSERTION
17	PRISM ROTATION
18	ANIMATION DISC INSERTION
19	ANIMATION DISC ROTATION
20	FROST
21	FOCUS
22	ZOOM
23	PAN
24	PAN FINE
25	TILT
26	TILT FINE
27	RESET
28	FUNCTION

**DMX Chart: ClayPaky B-Eye K10**

1	RED
2	RED FINE
3	GREEN
4	GREEN FINE
5	BLUE
6	BLUE FINE
7	WHITE
8	WHITE FINE
9	LINEAR CTO
10	MACRO COLOUR
11	STROBE
12	DIMMER
13	DIMMER FINE
14	PAN
15	PAN FINE
16	TILT
17	TILT FINE
18	FUNCTION
19	RESET
20	ZOOM
21	SHAPE SELECTION
22	SHAPE SPEED
23	SHAPE FADE
24	SHAPE R
25	SHAPE G
26	SHAPE B
27	SHAPE W
28	SHAPE DIMMER
29	BACKGROUND DIMMER
30	SHAPE TRANSITION
31	SHAPE OFFSET
32	FOREGROUND STROBE
33	BACKGROUND STROBE
34	BACKGROUND SELECT

**DMX Chart: JB-Lighting JBLED A4 S16**

- 1 Pan
- 2 Pan fine
- 3 Tilt
- 4 Tilt fine
- 5 Control (000-007 full RGB, 008-015 white 8500K, 016-023 white 6500K, 208-215 Camera 50Hz Mode, 216-223 Camera 60Hz Mode, 224-231 Camera Flex Mode, 240-247 Reset after 2sec)
- 6 Strobe
- 7 Dimmer
- 8 Zoom (12° to 36°)
- 9 Red
- 10 Red fine
- 11 Green
- 12 Green fine
- 13 Blue
- 14 Blue fine
- 15 CTC
- 16 virtual color wheel (000-001 RGB Color Mix, above no RGB Mixing - only color wheel)
- 17 Speed Pan/Tilt
- 18 Speed Effects
- 19 Blackout Move (096-127 MIB at Movement, 128-159 MIB at Colorchange, 224-255 MIB at Movement&Colorchange. Fadetime per Setting from 5sec. to 0,1sec.)

**DMX Chart: Elation Platinum Spot LED**

- 1 Pan
- 2 Pan fine
- 3 Tilt
- 4 Tilt fine
- 5 Color Wheel
- 6 rot. Gobo Wheel
- 7 Gobo rotation & index
- 8 fixed. Gobo Wheel
- 9 Prism (0-31 open, 32-63 3facet, 64-95 5facet, 96-127 Frost, 128-255 shitty macros)
- 10 Prism rotation
- 11 Focus
- 12 Shutter/Strobe
- 13 Dimmer
- 14 Iris
- 15 Speed Pan/Tilt (0-225 max to min, 226-235 MIB at movement, 236-245 MIB at anything)
- 16 Control (80-84 complete Reset, 85-87 Movement Reset, 88-90 Color Reset, 91-93 Gobo Reset, 97-99 Other Reset, 100-239 shitty macros, 240-255 S2L Kids Birthday)

**DMX Chart: Magic Cube 3D**

- 1 Dimmer
- 2 Rot, alle Segmente
- 3 Grün, alle Segmente
- 4 Blau, alle Segmente
- 5 Rot, Segment 1 (falls 2-4=0)
- 6 Grün, Segment 1 (falls 2-4=0)
- 7 Blau, Segment 1 (falls 2-4=0)
- 8 Rot, Segment 2 (falls 2-4=0)
- 9 Grün, Segment 2 (falls 2-4=0)
- 10 Blau, Segment 2 (falls 2-4=0)
- 11 Rot, Segment 3 (falls 2-4=0)
- 12 Grün, Segment 3 (falls 2-4=0)
- 13 Blau, Segment 3 (falls 2-4=0)
- 14 Farbauswahl (0-5 ohne Funktion, 6-10 Farbe 1, 11-15 Farbe 2, 16-20, Farbe 3, .....  
..... 246-250 Farbe 49, 251-255 Farbe 50)
- 15 Programmauswahl (0-15 ohne Funktion, 16-23 Programm 2, 24-31 Programm 3,....  
...216-223 Programm 27, 224-231 Programm 28, 232-255 Musiksteuerung)
- 16 Ablaufgeschwindigkeit des ausgewählten Programms (Kanal 15=16-231)  
od. Empfindlichkeit des eingebauten Mikrofons (Kanal 25=232-255)
- 17 Strobe Effekt (0-10 Ohne Funktion, 11-255 Strobe-Effekt, Geschwindigkeit steigend)













